




85656275



IP20

quicklink

### KNX radio wall-transmitter 2gang flat quicklink Berker K.1, anthracite matt, lacquered

- reset function (to factory setting), easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory
- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system
- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- with configuration LED, with transmission status and battery status LED, red/green/orange
- with configuration button
- operating areas configurable as one or two-area operation
- with lithium coin cell battery 3 V type: CR 2430
- with dismantling protection
- toolless quicklink configuration using buttons and LED display, top and bottom operating areas are freely configurable
- for flat surface mounting and extension of combinations
- For radio remote control of all assigned KNX radio receivers.

#### Technical features

Operating voltage	3 V DC
Battery service life [years]	≈ 5
Radio transmission frequency	868,3 MHz
Radio protocol	KNX Radio
Transmitter duty cycle	1 %
Receiver category	2
Number of radio channels	4
Radio transmission power	< 10 mW
Radio transmission range (free field)	max. 100 m
Radio transmission range (building)	max. 30 m
Operating temperature	-5 ... 45 °C
Assembling height	14 mm

anthracite matt, lacquered