



85655226



IP20

quicklink

## KNX radio wall-transmitter 1gang flat quicklink anthracite velvety, lacquered

### Technical features

#### Functions

- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration button

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Frequency

Radio transmission frequency	868,3 MHz
------------------------------	-----------

#### Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

#### Measurement

Relative humidity (without condensation)	0 ... 65 % (without condensation)
--	-----------------------------------

#### Battery

Battery service life [years]	≈ 5
- with lithium coin cell battery 3 V type: CR 2430	

#### Materials

RAL colour	RAL 7021 - Black grey
Colour of design line	anthracite
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	velvety

#### Dimensions

Assembling height	14 mm
-------------------	-------

#### LED control

- with transmission status and battery status LED, red/green/orange
- with configuration LED

#### Installation, mounting

- for flat surface mounting and extension of combinations

---

**Connection**

---

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system
- 

**Settings**

---

- toolless quicklink configuration using buttons and LED display
  - top and bottom operating area are freely configurable
- 

**Equipment**

---

Number of radio channels	2
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

---

**Safety**

---

- with dismantling protection
- 

**Use conditions**

---

Operating temperature	-5 ... 45 °C
-----------------------	--------------

---

**Identification**

---

Application, usage	KNX radio- operating systems
Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

---